SIEMENS

MammoReport^{Plus}

SP

Installation Instructions

Installation of Extra Hard Drives

© Siemens AG 2005
The reproduction, transmission or use of this document or its contents is not permitted without express written authority. Offenders will be liable for damages. All rights, including rights created by patent grant or registration of a utility model or design, are reserved.

English
Print No.: SPB7-420.812.20.01.02
Doc. Gen. Date: 01.05

Replaces: n.a.

Chapter	Page	Revision
All	All	01

Document Revision Level

The document corresponds to the version/revision level effective at the time of system delivery.
Revisions to hardcopy documentation are not automatically distributed.

Please contact your local Siemens office to order current revision levels.

Disclaimer

The installation and service of equipment described herein is to be performed by qualified personnel who are employed by Siemens or one of its affiliates or who are otherwise authorized by Siemens or one of its affiliates to provide such services.

Assemblers and other persons who are not employed by or otherwise directly affiliated with or authorized by Siemens or one of its affiliates are directed to contact one of the local offices of Siemens or one of its affiliates before attempting installation or service procedures.

Copyright Notice

The DICOM functionalities in the MammoReportPlus system are based on the libraries from Merge Technologies Inc.

Celsius R610 is a trademark of Fujitsu Siemens Computers.

Windows XP Professional is a trademark of Microsoft Corporation.
SIMOMED SMM 21201P and syngo are trademarks of Siemens AG.

Softcopy reading software by MeVis BreastCare,
copyright © 2001 - 2005 by MeVis BreastCare.

Contents 0 - 1

Page

1 Prerequisites 1 - 1

Introduction . . . 1 - 1
Components Included . . . 1 - 1
Documents Required . . . 1 - 1
Tools Required . . . 1 - 1
Time Required . . . 1 - 1
Protective Measures . . . 1 - 2

2 Hard Drive Installation 2 - 1

Disconnect the Power Supply Cable . . . 2 - 1
Remove the Computer Access Panel . . . 2 - 1
SCSI ID Settings . . . 2 - 2
Installing the Hard Disk Drive . . . 2 - 3
Closing the Casing . . . 2 - 4
Attach Product Label . . . 2 - 4

3 Formatting New Disk 3 - 1

Formatting and Assigning Extra Hard Disk . . . 3 - 1
Moving Striped Volume from F:\ to G:\ . . . 3 - 1
Format New Disk . . . 3 - 1
Check Sharing and Access Rights . . . 3 - 2
Change Configuration of Virus Scanner (Optional) . . . 3 - 5
Configure the Safety Options and Settings . . . 3 - 5

4 Changes to Previous Version 4 - 1

Contents

Page

Introduction

These instructions describe how to install one extra 147 GB hard drive on the MammoReport^{Plus} workstation based on a Celsius R610 computer.

Components Included

The following parts are included in the MammoReport^{Plus} Expansion kit 8380268:

Quantity	Part no.	Name
1		147 GB Hard disc drive. 10k U320W-SCSI.
6		Jumpers for setting SCSI ID on Hard drives
1		Product label
1		Installation Instructions (this document)

Documents Required

Installation and Start-up Instructions (SPB7-420.814.20...)

Tools Required

Standard tool kit.

Time Required

Approximately two hours for one person.

Protective Measures

⚠WARNING

Risk of high voltage!

Disconnect the power supply cable of the computer before removing the computer access panel.

⚠CAUTION

The computer contains electrostatic highly sensitive components requiring particular care in their handling.

Risk of damaging components.

Make sure to follow the ESD guidelines.

Disconnect the Power Supply Cable

1. Shut down the operating system properly and turn off the computer and any external devices.
2. Disconnect the power supply cable of the computer.

Remove the Computer Access Panel

1. Remove the computer access panel, refer to Fig. 1.



Fig. 1 Remove the Access Panel.

⚠CAUTION

The computer contains electrostatic highly sensitive components requiring particular care in their handling.

Risk of damaging components.

Make sure to follow the ESD guidelines.

2. Slide the side cover approximately 2 cm (a) in the direction of the arrow (1), until the stop.
3. Unhook the upper edge of the side cover from the casing.
4. Pull the side cover in the direction of the arrow of the casing.

SCSI ID Settings

1. Set SCSI ID for the hard drive on contact J5. The hard drive should have SCSI ID 3. Refer to Fig.3.



Fig. 2 Jumper Settings for SCSI ID

Installing the Hard Disk Drive

1. Open the casing (see "Remove the Computer Access Panel").
2. Make the required settings at hard disk.
3. Secure the EasyChange rails on the side of the hard disk by inserting the upper pins of the EasyChange rail in the corresponding holes of the hard disk. Refer to Fig. 3



Fig. 3 Securing the EasyChange Rails



Fig. 4 Installing the Hard Disk Drive

4. Push the hard disk drive into the casing (1) right below the installed hard disks until the EasyChange rails engage.
5. Connect the data and power supply cables to the hard disk drive or to the hard disk drives.

NOTICE	**Connect the blue plug of the data cable to the connection on the mainboard. Connect the plug on the other end to the hard disk drive.**

NOTICE	**It may be necessary to modify the entry for the drive in the BIOS Setup.**

Closing the Casing



Fig. 5 Closing the Casing

1. Hook the side cover into the lower guide trail in the casing (1). Make sure that the side cover is offset by approximately 2 cm (a).
2. Engage the top edge of the side cover on the casing.
3. Push the side cover as far as it will go in the direction of the arrow (2).
4. Connect the power supply cable of the computer.Turn on the computer and start up the operating system.

Attach Product Label

1. Attach product label 34 34 008 on top of the workstation beside the product label of the workstation.

Formatting and Assigning Extra Hard Disk

The 3rd 147 GB data disk will be a separate partition F:\.

NOTICE	**Do not stripe this partition with the two existing disks.**

Moving Striped Volume from F:\ to G:\

1. Login as OS administrator.
2. Open with right mouse click My Computer ⇒ Manage ⇒ **Disk Management**.
3. Right mouse click on **volume (F:)** ⇒ Change Drive Letter and Paths ⇒ Change ⇒ **Assign … and select G:** from list.
4. **Change the drive name** via right mouse click ⇒ **Properties** from MED_DATA **to SCR_DATA**.

Format New Disk

1. **Format new disk** as **basic / simple / primary partition** (NOT STRIPED or SPANNED).
2. **Assign** drive letter **F:\,** name **MED_DATA** and perform **quick format**.
3. Exit computer management and open windows explorer.
4. **Move** syngo **image directory** from G:\image **to F:\image**.
5. Check that the **sharing symbol** appears in explorer.



Fig. 1 Symbol for Sharing

6. Edit **C:\MBCSCR\lightbox.ini** with Notepad and change all **paths** from F:\SCRData to **G:\SCRData**.

```
# LightBox Configuration

#
# Directories
#
Annotations:            +Annotations
CAD:                    +Cad
Database:               +Database
DICOM:                  G:\SCRDATA\dicom
DICOM_SR:               G:\SCRDATA\dicom_SR
DICOMImport:            G:\SCRDATA\DICOMIMPORT
Envelopes:              +Envelopes
Exports:                G:\SCRDATA\Exports
Help:                   +Help
Images:                 G:\SCRDATA\Images
Incoming:               +Incoming
Lut:                    +Lut
Internals:              +Internals
Log:                    C:\syngo\Log\MBCLog
Miniaturen:             G:\SCRDATA\Miniaturen
PrintSpool:             G:\SCRDATA\PrintSpool
Reports:                +Reports
UserPrefs:              +UserPrefs
SyngoBackupPath:        +syngoBackup
```

Fig. 2 Changed Lightbox.ini file

7. **Save** changes and **exit** editor.

Check Sharing and Access Rights

Check sharing for syngo image directory:

1. Select in windows explorer directory **F:\image**.
2. Open **context menu** with right mouse click and select **Sharing and Security...**
3. Check that sharing is set and sharing name is **IMAGES**.



Fig. 3 Share this Folder: IMAGES

4. Select button **Permissions** and check that all permissions are checked.



Fig. 4 Permissions for IMAGES

Check access rights for syngo images:

1. Change to tab **Security** and check that access rights are as shown in next figure.



Fig. 5 Access Rights to Folder IMAGE

2. If that is **not** the case **open a dos box** with Start ⇒ Run ⇒ enter **cmd** and press **enter** and give the following commands:

- "`cacls F:\IMAGE /T /P SiemensMed:F SYSTEM:F Administrators:F Administrator:F`". Answer the appearing question **Are you sure (Y/N)** with **Y**.
- "`cacls F:\IMAGE /T /G SiemensMed:F SYSTEM:F Administrators:F Administrator:F`". Answer the appearing question **Are you sure (Y/N)** with **Y**.

3. **Repeat point 1.** - it shall be now ok.
4. **Leave** the dialog with press button **OK**.

Set access rights for SCR image directory:

1. Open dos box with Start ⇒ Run ⇒ enter **cmd** and press **enter**.
2. Give command: "`cacls G:\SCRData /T /P Users:F SYSTEM:F Administrators:F Administrator:F SiemensMed:F`".
3. Answer the question **Are you sure? (Y/N)** with **Y**.
4. Give command: "`cacls G:\SCRData /T /G Users:F SYSTEM:F Administrators:F Administrator:F SiemensMed:`".
5. Answer the question **Are you sure? (Y/N)** with **Y**.
6. Select in windows explorer directory **G:\SCRData**.
7. Press right mouse button and select **Sharing and Security...**
8. Change to tab **Security**.
9. Check that access rights are as shown in next figure.



Fig. 6 Access Rights to Folder SCRData

10. Exit properties dialog.

Change Configuration of Virus Scanner (Optional)

If the customer has a safety package, the virus scanner is installed. You have to change the exclusion list of its configuration.

Configure the Safety Options and Settings

1. Click on the **virus scanner icon** on the **task bar** to open the **Office Scan Client** .



Fig. 7 Office Scan Client

2. Check that hard disk named SCR_DATA (G:) is shown.
3. Open menu ⇒ **Options** ⇒ **Exclusion List**.


Options
Manual Scan Real-time Scan Scheduled Scan Exclusion List
Click the New button to specify files and folders that will be excluded from real-time, manual, and scheduled scans.
File names\Folder names:
C:\Database
C:\AN_CDR_DIR
C:\MSSQLSERVER
F:\IMAGE
F:\SCRData
Example of file name: virus.exe
Example of folder name: c:\virus folder\infected files
OK Cancel Help

Fig. 8 Tab: Exclusion List

4. **Select** the line **F:\SCRData** and **delete it** via button (red cross on the right side).

5. Click the button **Add** beside the delete button and enter **G:\SCRData**.



Fig. 9 Final Folders Exclusion List

6. Press return key.
7. Click on **OK** to save the settings and **exit** Virus Scan Client.
8. **Restart** system.

Chapter	Page	Change
		Initial version

This page intentionally left blank.